

GCS1314TAA3

# 4-Port HDMI Secure KVM Switch (TAA)



- NIAP-Certified PP3.0  
Validated to Protection Profile v3.0 for Peripheral Sharing Switches
- CAC & Biometrics Support  
Dedicated peripheral port for authorized CAC readers only and supported Biometrics readers
- 4-Port HDMI Secure KVM Switch  
One USB console controls 4 secure computers

[Secure KVM Switch Series PP3.0 Flyer](#)

## 4-Port Secure HDMI KVM Computer Switch - Protection Profile 3.0

IOGEAR's 4-Port HDMI Secure KVM Switch is NIAP-certified and compliant with PP3.0 (Protection Profile for Peripheral Sharing Switch version 3.0) requirements, satisfying the latest security requisites set by the U.S. Department of Defense for peripheral sharing switches.

Common criteria compliance ensures maximum information security while sharing a single set of approved HID's - keyboards, mice, speakers, CAC readers, and Microsoft Biometric Readers - between multiple computers. Conformity with Protection Profile v3.0 certifies that non-approved USB peripherals will be rejected and cannot be connected to the Secure KVM, providing high-level security, protection, and data safekeeping.

- |  |   |
|--|---|
| <ul style="list-style-type: none"> <li>• NIAP-Certified PP3.0<br/>Validated to Protection Profile v3.0 for Peripheral Sharing Switches</li> <li>• CAC &amp; Biometrics Support<br/>Dedicated peripheral port for authorized CAC readers only and supported Biometrics readers<sup>1</sup></li> <li>• 4-Port HDMI Secure KVM Switch<br/>One USB console controls 4 secure computers</li> <li>• Superior 4K UHD Video Resolution</li> <li>• 1920 x 1080 (FHD); 4K UHD Resolution: 3840 x 2160 @30Hz</li> <li>• Port Selection via Push-Button for Enhanced Security<br/>Keyboard restrictions - OSD &amp; hotkey methods are not allowed</li> <li>• Isolated Channel per Port<br/>Unidirectional data flow restricts data leakage between connected computers</li> <li>• Active Chassis Intrusion Detection<br/>Compromising the unit's cover renders the switch inoperable</li> <li>• Tamper-Evident Seals<br/>Visually detect attempts to gain access to switch's internal components</li> </ul> | <ul style="list-style-type: none"> <li>• Tamper-Proof Hardware<br/>Integrated circuits are soldered directly onto the circuit board to hinder component sabotage</li> <li>• Non-Reprogrammable Firmware<br/>Prevents tampering and attempts to reprogram the switch's firmware</li> <li>• Clears Keyboard Buffer<br/>Data clears automatically after transmission to switch and resets</li> <li>• Analog Speaker Support</li> <li>• Secure audio data input does not convert digital audio to analog audio</li> <li>• Multiplatform Support<br/>Windows® 2000, Vista, 7, 8, 8.1, 10, Linux, Mac OS X, &amp; Sun</li> <li>• Rugged Metal Enclosure<br/>Durable, Full Metal Chassis</li> <li>• Build-In, Internal Power Supply</li> </ul> |
|--|---|
- <sup>1</sup>Compatible with Microsoft® LifeCam HD-3000 and Microsoft Fingerprint Reader. Please contact your Administrator for CAC and Biometric Reader authorization.





**Requirements**

**Package Contents**

- |  |   |
|--|---|
| <ul style="list-style-type: none"> <li>• <b>Console</b></li> <li>• HDMI monitor capable of the highest resolution that you will be using on any computer in the installation</li> <li>• Standard 104-key wired USB or PS/2 keyboard</li> <li>• Standard 2 or 3 button wired USB or PS/2 mouse</li> <li>• Speaker (optional)</li> <li>• USB Smart card or CAC (Common Access Card) reader (Optional)</li> <li>•</li> <li>• <b>Computers</b></li> <li>• An HDMI Video output connector</li> <li>• A USB Type A port for keyboard and mouse</li> <li>• A USB Type A port for Smart Card or CAC reader (Optional)</li> <li>• A 3.5mm jack Audio port for speaker (Optional)</li> <li>•</li> <li>• <b>Cables</b></li> <li>• Do not attach cables that has microphone or line-in audio input</li> <li>•</li> <li>• <b>Operating Systems</b></li> <li>• Windows 2000, Windows Vista, Windows 7, Windows 8, Windows 8.1, Windows 10</li> <li>• Linux: Kernel 2.6+, RedHat v6.0+, SuSE v8.2+, Mandriva (Mandrake) v9.0+</li> <li>• UNIX: AIX v4.3+, FreeBSD v3.51+, Sun Solaris v9+</li> <li>• Novell Netware v5.0+</li> <li>• Mac OS v9+</li> <li>• DOS v6.2+</li> </ul> | <ul style="list-style-type: none"> <li>• 1 x 4-Port Single View HDMI Secure KVM Switch</li> <li>• 1 x Power Cord</li> <li>• 1 x Manual</li> <li>• 1 x Warranty</li> </ul> |
|--|---|

Specifications

---

<b>Computer Connections</b>		<b>Unit Dimensions</b>	
Direct	4	Height	1.75" (4.45cm)
<b>Console Connection</b>	1 Direct	Length	13.25" (33.66cm)
<b>Port Selection</b>	Pushbutton	Depth	6.063" (15.4cm)
<b>Console Connectors</b>		<b>Unit Package Dimensions</b>	
Monitor	1 x HDMI 1.4 Female (Black)	Height	4.75" (12.07cm)
Keyboard	1 x 6-pin Mini-DIN Female (Purple); 1 x USB Type-A Female (Black)	Width	16.25" (41.27cm)
Mouse	1 x 6-pin Mini-DIN Female (Green); 1 x USB Type-A Female (Black)	Depth	8.25" (20.96cm)
Audio	1 x Mini Stereo 3.5mm Jack Female (Green)	<b>Master Carton</b>	
Microphone	N/A	Height	9.5" (24.13cm)
CAC	1 x USB Type-A Female (Black)	Width	17" (43.18cm)
<b>CPU Connectors</b>		Depth	15" (38.1cm)
Monitor	4 x HDMI 1.4 Female (Black)	Master Carton Qty.	3
Keyboard & Mouse	4 x USB Type-B Female (White)	<b>Weight</b>	
Audio	4 x Mini Stereo 3.5mm Jack Female (Green)	Master Carton Wt.	16.55lb (7.52kg)
Microphone	N/A	Unit Pack Wt.	4.70lb (2.14kg)
CAC	4 x USB Type-B Female (White)	Unit Wt.	3.74lb (1.70kg)
<b>Switches</b>			
F/W Upgrade	N/A		
Port Selection	4 x Pushbuttons		
Reset	1 x Semi-recessed Pushbutton		
Power	1 x Rocker		
<b>LEDs</b>			
On Line	4 x Orange		
Selected	4 x Orange		
CAC	4 x Green		
Power On	1 x Blue		
Key Lock	3 x Green (Num Lock, Caps Lock, Scroll Lock)		
Console Video	1 x Green (Rear Panel)		
<b>Emulation</b>			
Keyboard	USB		
Mouse	USB		
<b>Video Resolution</b>	Max. 3840 x 2160 @30Hz (UHD); 1920 x 1080 (FHD)		
<b>Scan Interval</b>	N/A		
<b>Power</b>			
Amps			
Voltage	100 - 240V, 50 - 60Hz		
<b>Environment</b>			
Operation Temperature	0 - 50C		
Storage Temperature	-20 - 60C		
Humidity	0 - 80% RH, Non-condensing		
<b>Housing</b>			
Case	Metal		

at Home at Work on-the-Go

